

Product data sheet HV gate valve, Series 140, DN 100 (ID 4") Ordering No. 14040-CE48

Description

Flange CF-F 100

Actuator Pneumatic, with 3-position actuator

with solenoid valvewith position indicator

Feedthrough Rotary feedthrough

Technical data

Leak rate - Valve body $< 1 \cdot 10^{-9}$ mbar Is⁻¹

– Valve seat < 1 · 10⁻⁰ mbar Is⁻¹</p>

Pressure range $1 \cdot 10^{-8}$ mbar to 2 bar (abs)

Differential pressure on the gate ≤ 2 bar

Differential pressure at opening \leq 30 mbar

Conductance (molecular flow) – Nominal 1 740 ls⁻¹

Min. adjustable
 5 ls⁻¹

Cycles until first service – Unheated and under 200 000

clean conditions

Temperature - Valve body ≤ 150 °C (Maximum values: depending on operating conditions and sealing materials) - Valve body ≤ 150 °C - Solenoid ≤ 50 °C - Position indicator ≤ 80 °C

Heating and cooling rate 50 °C h⁻¹

Material (main components) – Valve body AISI 304 (1.4301)

- Mechanism AISI 304 (1.4301), AISI 301 (1.4310)

Seal – Bonnet FKM (Viton®), vulcanized

– Gate
 – Actuator
 FKM (Viton®), O-ring
 FKM (Viton®), NBR

Mounting position any

Volume of pneumatic actuator 0.53 I / 0,019 ft³

Compressed air 4-7 bar / 58-102 psi

min. - max. overpressure

Compressed air connection G1/8" (1/8" NPT for USA)

Actuation time - closing $\leq 2.5 \text{ s}$

- opening ≤ 2.5 s

Weight 17 kg / 37 lbs

Created by: NIW	Release date: 24.10.2020	1/2
Modified by:	Release date:	877606EA



Product data sheet HV gate valve, Series 140, DN 100 (ID 4") Ordering No. 14040-CE48

Behavior in case of compressed

air pressure drop

Valve closedValve remains closedValve openundefined

– Valve open– Middle positionundefined

Behavior in case of power failure

Valve closed
Valve remains closed
Valve closes
Middle position
valve closes

Valve position indication

visual (mechanical)


Electrical connections

Solenoid valve (2x)

Type 5/2 way

Voltage Defined by order

Power consumption 2.5 W




Wiring diagram

Position indicator

Type Micro switch

Voltage \leq 250 V AC \leq 50 V DC

Current max. $\leq 5 \text{ A} \leq 3 \text{ A}$



Wiring diagram

Created by: NIW	Release date: 24.10.2020	2/2
Modified by:	Release date:	877606EA